

SWP1708TS

Compact

17-input compact multiswitch with 8 output taps; DIP switch to select active and passive TV gain.



Technical Chars

- Satellite band up to 2300MHz.
- **High output level** to cover long cable distances(60m with 6.7mm cable).
- Each port has an LED to show correct reception of DiSEqC commands.
- Return channel included when TV gain is passive (5-65MHz).
- **When TV gain is passive, the product is fully powered by the receivers**, the power supply only serves to power the active TV gain, other amplifiers and LNBs.
- **External PSU1340TS power supply** (13V, 4A) included in **the package** with Male Jack connector (2.1x5.5x12; inside positive, outside negative); to optimise installation space and reduce maintenance time.
- Small size due to matrix switching system, with connectors on both sides.
- Easy to install thanks to standard input colouring.

SWP1708TS		
Code		287355
Inputs		16 SAT, 1 TV
Taps		8
SAT		
Bandwidth	MHz	950-2300
Gain	dB	-4/0
Max Output level	dBμV	100
TV		
TV bandwidth	MHz	Active TV: 47-862; Passive TV: 5-862
Gain (Active)	dB	0
Gain (Passive)	dB	-20
Max Output level	dBμV	Active TV: 95
Return channel		
Bandwidth	MHz	Passive TV: 5-65