

Radio DAB Antenna Radijska DAB antena

DAB-4+ F

- ✓ **It is used for digital DAB (DAB & DAB+ Digital Audio Broadcast) radio signals reception in the vertical polarization, (frequency range 170 - 240 MHz)**
Uporablja se za sprejem DAB (DAB in DAB+ Digital Audio Broadcast) radijskih signalov v vertikalni polarizaciji (frekvenčni pas 170 - 240 MHz)
- ✓ **Impedance 75 Ohm, antenna carrier 18x18 mm.**
Impedanca 75 Ohm, nosilec antene 18x18 mm.
- ✓ **Can be used for both horizontal or vertical polarization.**
Primerna za horizontalno ali vertikalno polarizacijo.
- ✓ **Reliable and robust design for optimum performance and long life time.**
Zanesljiv in robusten dizajn za optimalno delovanje in dolgo življenjsko dobo.



Technical data / Tehnični podatki :

Type Tip	Freq. range Frekv. področje	No. of elements Število elementov	Gain Dobitek	F/B ratio Razmerje napr.-naz.	Beam width Širina glav. lista	Antenna length Dolžina antene	Connection Priključek	Packing Pakiranje	
								pcs. kos	cm / m3 cm / m3
DAB-4+ F	170 - 240 MHz	4	5,5 - 6,5 dB(i)	14 - 18 dB	V 65°	81 cm	"F"		

